

Linortek Netbell®-KL All-In-One Extra Loud Break Bell System

*Self-Contained, Easy-To-Use, Remote Access, Scheduling Bells from Web Browser,
No Software Required to Install on Your Computer*

The Key Features

- **Easy to Install:** The Netbell system is low voltage system that's designed for DIY installation, no need to hire professional installer
- **Web-based control:** Access, schedule, and manage your break bells from any computer on the network
- **Programmable up to 500 events:** Create schedules for breaks and shift changes, automated reminders from standard browser
- **High-output loud bell:** Up to 102dB@1m ensures your alerts are heard even in the noisiest environments
- **Flexible scheduling:** Week-day or calendar-based bell scheduling giving you the flexibility of bell control
- **Easy to Expand:** Each Netbell is an independent system, that you can easily add more units to the existing system as your business grows.
- **Designed, developed and built in the USA**
- Scan the QR code to learn more:



Linortek Netbell® is a network-enabled, affordable, reliable, and easy-to-deploy timed alert system. With the easy-to-use built-in web interface, you can access, control, and schedule bells, equipment, or any other timed events over the network from a web browser. No additional software or designated computer is required, eliminating the need for complex wiring and control systems. This cost-effective solution is ideal for schools, factories, warehouses, and other facilities to signal start and stop work, lunch breaks, shift changes, as well as using it as employee alarm system to satisfy the requirements of OSHA 29 CFR 1910.165 regulation.

The Netbell-KL is a self-contained, all-in-one extra loud bell system. This easy-to-use bell system was designed for busy school administrators, factory/warehouse operations, and maintenance managers to save valuable time in setting up a break time alarm system. It comes with a built-in 6-inch high output bell (102dB) that can cover up to 20,000 square feet area, and a completely wired web-based bell controller installed within a NEMA-rated box. All software and mounting hardware required for installation and operation are included; no additional parts are needed. There is one external bell output that allows you to add one more bell (not included) as your business expands. With the digital input, you can wire a push switch to ring the bell manually in an emergency.

Netbell® Technical Specifications

Netbell-KL All-In-One Extra Loud Bell System

General Information

Model	Netbell-KL	Netbell-KL-M2	Netbell-KL-E1	Netbell-KL-E2M
Part#	01-910-00029	01-910-00043	01-910-00050	01-910-00051

Technical Specification

Bell Scheduling Software	Built- In (All software located on built-in web server.)			
Event Schedules	Up to 500 Web-Based Event Schedules (Add schedules from web browser)			
Bell Ringing Duration	User Programmable for Each Schedule			
Built-In Bell (6", 102dBa@1m)	1			
External Bell Output (s)	1	2	1	2
External Bell (s) (6", 102dBa@1m)	0	0	1	2
Coverage (SQ FT)	20,000	20,000	40,000	60,000
Manual Bell Control	Yes			
Push Switch	Optional			
Enclosure	ABS, IP66 /150mm x 150mm x 90mm			
Accessories	Power Cable/RJ45 Cable/Mounting Brackets			
Power Input	24VAC (included)			
Voltage Sensor	On Board			
Temperature Sensor	On Board			
Rechargeable Battery	On Board (For offline time & settings keeping backup up to 7 days)			
Working Temperature	From 0 to +60 Celsius			
Supported Protocols	HTTP/ SMTP/SNTP			