

SUPERING BELLS® - SINGLE STROKE

BELLS AND BELLING
SUPERING® BELLS - SINGLE STROKE



- Includes Gong Shell
- Efficient Operation
- Universal Backplate
- Variety of Applications

SUPERING® BELLS - SINGLE STROKE

Single Stroke bells produce one strike (tone) when power is applied and will not repeat until power is removed and then re-applied. The W.L. Jenkins line of single stroke bells include indoor Pig-Tail and Plug-In types, in AC and DC voltages.

FEATURES

- Completely assembled with gong shell
- Universal backplate for mounting to various backboxes
- Gong shell need not be removed for installation
- Efficient operation
- Available in 4 1/4", 6", 8" and 10" gong sizes
- Indoor models

APPLICATIONS

Single Stroke bells have applications in paging and coding systems where a defined number of strikes (tones) can be generated and identified by the system:

- **Institutions** coded evacuation, time clock and paging systems
- **Recreational Equipment** gaming equipment, toys, and childrens' trains
- **Transportation Conveyance Systems** trolley cars, trams, trains, ferries and hydrofoils
- **Maritime Signaling**

See other side for ordering information and specifications



The W.L. Jenkins Company
1445 Whipple Ave., S.W. • Canton, Ohio 44710-1321
330-477-3407 •
www.wljenkinsco.com

SUPERING BELLS® - SINGLE STROKE

Ordering Information and Specifications

SUPERING® BELLS - SINGLE STROKE

AC - PIG-TAIL - INDOOR - 50-60 hertz

Volts	Ohms	Amps	Gong Size & Model Number			
			4 1/4"	6"	8"	10"
			INDOOR	INDOOR	INDOOR	INDOOR
12	2.50	2.2	1103	2103	3103	4103
24	7.5	1.2	1104	2104	3104	4104
120	170	0.35	1105	2105	3105	4105
240	890	0.15	1106	2106	3106	4106
32	7.5	2.0	1107	2107	3107	4107
48	35	0.7	1108	2108	3108	4108
60	35	0.9	1109	2109	3109	4109
Decibels at 10 Ft.			77-80	78-82	79-83	80-84
Weight			2.5#	3.5#	5.0#	6.5#

DC - PIG-TAIL - INDOOR

Volts	Ohms	Amps	Gong Size & Model Number			
			4 1/4"	6"	8"	10"
			INDOOR	INDOOR	INDOOR	INDOOR
12	7.5	1.5	1303	2303	3303	4303
24	35	0.6	1304	2304	3304	4304
120	700	0.15	1305	2305	3305	4305
240	2025	0.09	1306	2306	3306	4306
32	35	0.9	1307	2307	3307	4307
48	35	1.2	1308	2308	3308	4308
60	170	0.45	1309	2309	3309	4309
Decibels at 10 Ft.			77-80	78-82	79-83	80-84
Weight			2.5#	3.5#	5.0#	6.5#

AC - PLUG-IN - INDOOR - 50-60 hertz

Volts	Ohms	Amps	Gong Size & Model Number			
			4 1/4"	6"	8"	10"
			INDOOR	INDOOR	INDOOR	INDOOR
12	2.25	2.2	1113	2113	3113	4113
24	7.5	1.2	1114	2114	3114	4114
120	170	0.35	1115	2115	3115	4115
240	890	0.15	1116	2116	3116	4116
32	7.5	2.0	1117	2117	3117	4117
48	35	0.7	1118	2118	3118	4118
60	35	0.9	1119	2119	3119	4119
Decibels at 10 Ft.			77-80	78-82	79-83	80-84
Weight			2.5#	3.5#	5.0#	6.5#

DC - PLUG-IN - INDOOR

Volts	Ohms	Amps	Gong Size & Model Number			
			4 1/4"	6"	8"	10"
			INDOOR	INDOOR	INDOOR	INDOOR
12	7.5	1.5	1313	2313	3313	4313
24	35	0.6	1314	2314	3314	4314
120	700	0.15	1315	2315	3315	4315
240	2025	0.09	1316	2316	3316	4316
32	35	0.9	1317	2317	3317	4317
48	35	1.2	1318	2318	3318	4318
60	170	0.45	1319	2319	3319	4319
Decibels at 10 Ft.			77-80	78-82	79-83	80-84
Weight			2.5#	3.5#	5.0#	6.5#

Patents # 3,550,118; 3,424,124; 841,320; 841,321; 853,447



The W.L. Jenkins Company
1445 Whipple Ave., S.W. • Canton, Ohio 44710-1321
330-477-3407 •
www.wljenkinsco.com